

Linortek Netbell® -K All-In-One Network Bell System

Applications

Provide remote access to control timed alert system for:

- Schools
- Factories
- Office Buildings
- Warehouses
- Any other places need a timed alert system for breaks, shift changes or general alarms

The Key Features

- All-in-one system for easy installation, mounting hardware and cables are included, plug it in and add your schedules, you are all set
- no additional software or designated computer required
- Built-in Netbell™ server with up to 500 event schedules
- Different duration types for different events
- Import/export schedules from existing data in text format
- Flexible and accurate control of when the bells ring (HH:MM:SS, SUNDAY- SATURDAY)
- Built-in real time clock sync its time from NTP server
- Program and web page interface are upgradable over the internet
- Use as either a network device or a standalone device
- Designed, developed and made in USA

Self-Contained, Easy-To-Use, Remote Access, Scheduling Bells Over the Network, No Additional Software or Designated Computer Required



Linortek Netbell® is an ease-of-use, networked, custom developed device for schools, factories and other organizations to build a fully automated web-based timed alert system for signaling shift changes, general alarms, and breaks. The system is built on a TCP/IP platform with a built-in web server. This allows a user to access, control, and schedule the Bells or buzzers from anywhere over the network with no additional software or programming required.

The Netbell-K is a compact, self-contained design that was created with ease-of-use in mind. Intended to be an all-in-one solution, the Netbell-K features a high quality 6 inch high output bell (86dB) and a completely wired web-based bell controller installed within a NEMA-rated box, all software and mounting hardware required for installation and operation are included. There are one external bell output with CP connectors that provides quick connect /disconnect two external bells (not included) if you have a larger area needs to be covered. With the digital inputs you can wire a push switch for ringing bells manually in emergency.

For anyone who has separate areas or multiple buildings where running additional wiring is not an option, but network is available at the locations, you can use the built-in remote feature to manage & schedule multiple Netbell devices from one easy-to-use interface, without the need of hard-wiring the bells to a central control station, making the management of your bell systems incredibly easy.

Netbell® Technical Specifications

General Information

Model	Netbell-K	Netbell-K-M2	Netbell-K-E1	Netbell-K-E2M
Part#	01-910-00013	01-910-00036	01-910-00045	01-910-00013

Technical Specification

Web Server	Built- In (All software located on built-in web server.)			
Event Schedules	Up to 500 Web-Based Event Schedules (Add schedules from web browser)			
Bell Ringing Duration	User Programmable for Each Schedule			
Built-In Bell/Buzzer	1 (6" Bell/86dBa)			
External Bell (s)	0	0	1	2
Coverage (SQ FT)	8000	8000	16000	24000
Manual Bell Control	Yes			
Push Switch	1 (Included)			
Enclosure	ABS, IP66 /150mm x 150mm x 90mm			
Accessories	3M Power Cable/3M RJ45 Cable/Mounting Brackets			
Power Input	12VAC (included)		12VAC for the Main Controller, 12VDC for External Bell (included)	
Voltage Sensor	On Board			
Temperature Sensor	On Board			
Rechargeable Battery	On Board (For offline time & settings keeping backup up to 7 days)			
Working Tempera-	From 0 to +60 Celsius			
Supported Protocols	HTTP/ SMTP/SNTP			