

Netbell-NTG Tone Generator Technical Specifications

General Information

Model	Netbell-NTG	Netbell-NTG-08	Netbell-NTG-12	Netbell-NTG-C
Part#	01-910-00059	01-910-00067	01-910-00069	01-910-00080
Technical Specification				
Web Server	Built- In (All software located on built-in web server.)			
Event Schedules	Up to 500 Web-Based Event Schedules (Add schedules from web browser)			
Tone/Message Duration	User Programmable for Each Schedule			
Built-In Tones	40 Standard Tones			
Upload Custom Sounds	Yes			
Relay Output(s)	2 (Connect physical bells)	0	0	2 (Connect physical bells)
Digital Inputs	4 (Trigger special events)	0	0	4 (Trigger special events)
Audio Output	1 Stereo Line Output (30ohm)			
Speakers	0	1 (8", built-in)	1 (12", built-in)	2-50 (User selectable)
Amplifier	NA	1 (Built in)	1 (Built in)	1
Coverage (SQ FT)	NA	20,000	25,000	8,000-400,000
Play Background Music	Yes (from existing PA system)	Yes	Yes	Yes
Live Announcement	Yes (from existing PA system)	No	No	Yes
Audio File Format	Ogg Vorbis audio format			
Audio File Resolution	16bit/8bit			
Audio File Rate	44.1K/22K/11K/			
File Storage Size	1G (Record custom tones for up to 10 hours)			
Enclosure	Polycarbonate 125X175X60MM	ABS Impact-Resistant Nylon Fiber Cabinet		Polycarbonate 125X175X60MM (for Controller)
Accessories	3M RJ45 Cable/3ft: RCA, 3.5mm Audio, 4-CDR Cable	3M RJ45 Cable/1.5M AC Power Cord/Wall Mount Speaker Bracket		3M RJ45 Cable/3ft: RCA, 3.5mm Audio, 4-CDR Cable
Power Input	12VDC (included)	110VAC		Controller 12VDC (included), Amplifier: 110VAC
Voltage Sensor	On Board			
Temperature Sensor	On Board			
Rechargeable Battery	On Board (For offline time & settings keeping backup up to 7 days)			
Working Temperature	From 0 to +60 Celsius			
Supported Protocols	HTTP/ SMTP/SNTP			